

REOMED Isonet Network isolator

for copper-wire bound Ethernet networks



Technical Data

- Isolation voltage : 4 kV
- Insertion loss : -1,3 dB max.
- Return loss : - 8 dB min.

The REOMED Isonet network isolator is used for electrical isolation of devices in copper wire-bound Ethernet networks.

The isolation protects equipment and people from the effects of possible electrical voltage spikes on power supplies.

Potential equalization currents on the shielding of the network cable are reliably prevented.

Advantages

- Protection in both transfer directions
- Interruption of the shield connection of the network cable
- No additional power supply required
- No software installation required
- Maintenance-free
- RoHS compliant
- EN 60950-1
- EN 60601-1

Technical data	
Isolation voltage	4 KV
Input / output connector	RJ45
Supported network protocols	10BaseT, 100BaseTx, 1000BaseT
Insertion loss	-1,3 dB max.
Return loss	-8 dB min.
Protection	IP 20
Max. voltage of the connected devices	250 Vac rms
Operating temperature	-10 bis +70°C
Storage temperature	-40 bis +85°C
Humidity	10 bis 90% (without condensation)
Housing	Plastic
Weight	45 g
Dimensions (B x H x T)	25mm x 66mm x 40mm



REO AG

Brühler Straße 100 · D-42657 Solingen
Tel.: +49 (0)212 8804 0 · Fax: +49 (0)212 8804 188

E-Mail: info@reo.de
Internet: www.reo.de

■ Divisions:

▶ REO Vibratory Feeding and Power Electronics Division

REO Vibratory Feeding and Power Electronics Division
Brühler Straße 100 · D-42657 Solingen
Tel.: +49 (0)212 8804 0 · Fax: +49 (0)212 8804 188
E-Mail: info@reo.de

▶ REO Train Technologies Division

REO Train Technologies Division
Erasmusstraße 14 · D-10553 Berlin
Tel.: +49 (0)30 3670236 0 · Fax: +49 (0)30 3670236 10
E-Mail: zentrale.berlin@reo.de

▶ REO Drives Division

REO Drives Division
Holzhausener Straße 52 · D-16866 Kyritz
Tel.: +49 (0)33971 485 0 · Fax: +49 (0)33971 485 90
E-Mail: zentrale.kyritz@reo.de

▶ REO Medical and Current Transformer Division

REO Medical and Current Transformer Division
Schuldholzinger Weg 7 · D-84347 Pfarrkirchen
Tel.: +49 (0)8561 9886 0 · Fax: +49 (0)8561 9886 40
E-Mail: zentrale.pfarrkirchen@reo.de

▶ REO Test and PowerQuality Division

REO Test and PowerQuality Division
Brühler Straße 100 · D-42657 Solingen
Tel.: +49 (0)212 8804 0 · Fax: +49 (0)212 8804 188
E-Mail: info@reo.de

PRODUCTION + SALES:

■ China

REO Shanghai Inductive Components Co., Ltd
E-Mail: info@reo.cn · Internet: www.reo.cn

■ India

REO GPD INDUCTIVE COMPONENTS PVT. LTD
E-Mail: info@reogpd.com · Internet: www.reo-ag.in

■ USA

REO-USA, Inc.
E-Mail: info@reo-usa.com · Internet: www.reo-usa.com

SALES:

■ France

REO VARIAC S.A.R.L.
E-Mail: reovariac@reo.fr · Internet: www.reo.fr

■ Great Britain

REO (UK) Ltd.
E-Mail: main@reo.co.uk · Internet: www.reo.co.uk

■ Italy

REO ITALIA S.r.l.
E-Mail: info@reitalia.it · Internet: www.reitalia.it

■ Poland

REO CROMA Sp.zo.o
E-Mail: croma@croma.com.pl · Internet: www.croma.com.pl

■ Spain

REO ESPAÑA 2002 S.A.
E-Mail: info@reospain.com · Internet: www.reospain.com

■ Switzerland

REO ELEKTRONIK AG
E-Mail: info@reo.ch · Internet: www.reo.ch

■ Turkey

REOTURKEY ELEKTRONIK San. ve Tic. Ltd. Şti.
E-Mail: info@reo-turkey.com · Internet: www.reo-turkey.com